

COMPATIBILITY EXCEPTIONS

Type of control panel (CP)	JA-100Kxx	JA-101Kxx	JA-103Kxx	JA-106Kxx	JA-107Kxx
CP overview	JA-100K JA-100KR	JA-101K JA-101KR JA-101KR-LAN JA-101KR-LAN-3G	JA-103K JA-103KRY	JA-106K JA-106K-3G JA-106KR JA-106KR-3G	JA-107K JA-107KRY
Radio module as a part of the CP	JA-100KR	JA-101KR JA-101KR-LAN JA-101KR-LAN-3G	JA-103KRY	JA-106KR JA-106KR-3G	JA-107KRY
Radio module JA-111R in CP	✓ Can only be connected to the bus terminal block. PLV-JA111R must be purchased with an included connector.	✓ Can only be connected to the bus terminal block. PLV-JA111R must be purchased with an included connector.	✓ Connecting cable is part of CP.	✓ Can only be connected to the bus terminal block. PLV-JA111R must be purchased with an included connector.	✓ Connecting cable is part of CP.
Radio module JA-110R	✓	✓	✓ JA-110R from version FW LR61601 and higher.	✓	✓ JA-110R from version FW LR61601 and higher.
GSM communicator As a part of CP	✗	✓	JA-103KRY	✓	JA-107KRY
GSM communicator as a module JA-190Y	✓	✗	✗	✗	✗
GSM communicator as a module JA-192Y	✗	✗	JA-103K	✗	JA-107K
LTE communicator as a module JA-194Y	✗	✗	JA-103K	✗	JA-107K
3G GSM communicator	✗	JA-101KR-LAN-3G	✗	JA-106K-3G JA-106KR-3G	✗
PSTN-Modul JA-190X	✓	✓	✗	✓	✗

Type of control panel (CP)	JA-100Kxx	JA-101Kxx	JA-103Kxx	JA-106Kxx	JA-107Kxx
LAN communicator	✓	JA-101KR-LAN JA-101KR-LAN-3G	✓	✓	✓
JA-110E / JA-150E keypads	✓	✓	✓	✓	✓
JA-112E/JA-152E JA-113E/JA-153E JA-114E/JA-154E keypads	✗	✓	✓ JA-112E from version FW LU61501 and higher JA-113E from version FW LU61601 and higher	✓	✓ JA-112E from version FW LU61501 and higher JA-113E from version FW LU61601 and higher
New 2-way devices, e.g.: JA-152P, JA-152P (G), JA-152M, JA-155P, JA-162PW, JA-162PW (G)	✗	✗	✓	✗	✓
JA-180A outdoor siren	✓	✓	✗	✓	✗
JA-154J key fob (no MS)	✓	✓	✗	✓	✗
JA-118N	✓	✓	✓ From version LY68003 and higher lower versions only in max. range in F-Link of PG 32	✓	✓ From version LY68003 and higher lower versions only in max. range in F-Link of PG 32
JA-110I / JA-110N-DIN	✓	✓	✓ Only in max. range in F-Link of 32 PG	✓	✓ Only in max. range in F-Link of 32 PG